

## 感应电动机 Induction Motors

### 60W

□90mm



### 规格Specs 连续额定Cont. Rated

型号Model · 类型Type 上段:齿轮轴 Upper: Pinion Shaft 下段()内:圆轴Below: Round Shaft		输出功率 Output Power W	电压 Voltage V	频率 Frequency Hz	电流 Current A	启动转矩 Starting Torque mN.m	额定转矩 Rated Torque mN.m	额定转速 Rated Speed r/min	电容器容量 Capacitor μF
导线型 Lead Wire Type 外形图Dimensions①	带端子箱型 Terminal Box Type 外形图Dimensions②								
5IK60GN-AFJ (5IK60A-AFJ)	5IK60GN-AFTJ (5IK60A-AFTJ)	60	1ph100	50	1.00	320	470	1250	20.0
				60	1.10		380		
5IK60GN-EFJ (5IK60A-EFJ)	5IK60GN-EFTJ (5IK60A-EFTJ)	60	1ph110 1ph120	60	0.80	300	380	1550	12.0
					0.85				
5IK60GN-CFE (5IK60A-CFE)	5IK60GN-CFTE (5IK60A-CFTE)	60	1ph220 1ph230	50	0.50	340	470	1250	4.0
					0.55				
5IK60GN-HFE (5IK60A-HFE)	5IK60GN-HFTE (5IK60A-HFTE)	60	1ph220 1ph230	60	0.50	340	380	1550	
					0.55				
5IK60GN-SF (5IK60A-SF)	5IK60GN-SFT (5IK60A-SFT)	60	3ph220	50	0.45	1000	470	1250	
				60	0.40	800	380	1550	-

- 电动机铭牌上的型号并无表示电容器种类的(J、E)记号。  
With the name on record on the motor nameplate, there is no capacitor types(J、E) marked.
- 各种安全规格以电动机铭牌上的型号取得认证。  
When the motor is approved under various safety standards, the model name on the nameplate is the approved model name.

### 种类/Type

电动机/Motor

类型 Type	型号Model	
	齿轮轴型 Pinion Shaft	圆轴型 Round Shaft
导线型 Lead Wire Type	5IK60GN-AFJ	5IK60A-AFJ
	5IK60GN-EFJ	5IK60A-EFJ
	5IK60GN-CFE	5IK60A-CFE
	5IK60GN-HFE	5IK60A-HFE
	5IK60GN-SF	5IK60A-SF
带端子箱型 Terminal Box Type	5IK60GN-AFTJ	5IK60A-AFTJ
	5IK60GN-EFTJ	5IK60A-EFTJ
	5IK60GN-CFTE	5IK60A-CFTE
	5IK60GN-HFTE	5IK60A-HFTE
	5IK60GN-SFT	5IK60A-SFT

平行轴减速器 (另售)  
Parallel Shaft Gearhead(Sold Separately)

减速器种类 Gearhead Type	减速器型号 Gearhead Model	减速比Gear Ratio
长寿命·低噪音 Long Life·Low Noise	5GN□K	3、3.6、5、6、7.5、9、12.5、15、18、25、30、36、50、60、75、90、100、120、150、180、200
	5GN10XK(中间减速器Decimal Gearhead)	

- 减速器型号的□中为减速比的数值  
Enter the gear ratio in the box (□) within the model name